


Merlin®



gomerlin.com.au
gomerlin.co.nz



MJ3800

Residential Sectional Garage Door Opener

Installation and Operating Instructions

Owners Copy: Please keep these instructions for future reference



This manual contains **IMPORTANT SAFETY** information
DO NOT PROCEED WITH THE INSTALLATION BEFORE READING THOROUGHLY



START BY READING THESE IMPORTANT SAFETY INSTRUCTIONS

WARNING

- Failure to comply with the following instructions may result in serious personal injury or property damage.
- Read and follow all instructions carefully.
- The garage door opener is designed and tested to offer safe service provided it is installed and operated in strict accordance with the instructions in this manual.



These safety alert symbols mean **WARNING** : A possible risk to personal safety or property damage exists.



Keep garage door balanced. Do not let the garage door opener compensate for a binding or sticking garage door. Sticking, binding or unbalanced doors must be repaired before installing this opener.



Do not wear rings, watches or loose clothing while installing or servicing a garage door opener. Wear gloves, safety goggles and suitable protective clothing where appropriate.



Frequently examine the door installation, in particular cable, springs and mountings for signs of wear, damage or imbalance. Do not use if repair or adjustment is needed since springs and hardware are under extreme tension and a fault can cause serious personal injury.



To avoid serious personal injury from entanglement, **remove all ropes, chains and locks connected to the garage door** before installing the door opener.



Installation and wiring must be in compliance with your local building and electrical codes.



The safety reverse system test is very important. Your garage door **MUST** reverse on contact with a 40 mm obstacle placed on the floor. Failure to properly adjust the opener may result in serious personal injury from a closing garage door. **Repeat the test once a month and make any necessary adjustments.**



This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.



Use the **Manual Release** only for the separation of the carriage from the drive and - if possible - **ONLY** with the door closed. Do not use the red handle to push the door up or pull it down. Operation of the emergency release can lead to uncontrolled movements of the door, if springs are weak or broken or if the door is unbalanced. Mount the release handle of the emergency release at a height less than 1.8 m from the floor.



The Protector System™ must be used for all installations where the closing force as measured on the bottom of the door is over 400 N (40 kgf). Excessive force will interfere with the proper operation of the Safety Reverse System or damage the garage door.

SPECIAL NOTE: Merlin strongly recommends that The Protector System™ be installed on all garage door openers.



After installation, ensure that the parts of the door do not extend over public footpaths or roads.



Install the wireless wall control (or any additional wall control) **in a location where the garage door is visible, at a height of at least 1.5 m and out of the reach of children. Do not allow children to operate push button(s) or transmitter(s).** Serious personal injury from a closing garage door may result from misuse of the opener.



Permanently fasten the Warning Labels in Prominent Places, adjacent to Wall Controls and on manual release mechanism as a reminder of safe operating procedures.



Activate opener only when the door is in full view, free of obstructions and the opener is properly adjusted. No one should enter or leave the garage while the door is in motion.



Automatic Door- The door may operate unexpectedly, therefore do not allow anything to stay in the path of the door.



Do not allow children to play near the door, or with door controls. Keep remotes away from children.



Disconnect electric power to the garage door opener before making repairs or removing covers.



If the supply cord is damaged, it must be replaced by the manufacturer, its service agent or similarly qualified persons in order to avoid hazard.



This opener should not be installed in a damp or wet space exposed to weather.



To avoid damage to very light doors (such as fibreglass, aluminium or steel doors), an appropriate reinforcement should be added. To do so, contact the door manufacturer.

SAVE THESE INSTRUCTIONS


NOTE: A model CM475 EverCharge™ Battery Backup Unit (BBU) is strongly recommended if there is no access door to the building, as this opener cannot be used in conjunction with an external emergency release mechanism.

CONTENTS	PAGE
SAFETY INSTRUCTIONS	2
CARTON INVENTORY	3
ACCESSORIES	3
SPECIFICATION	4
TOOLS REQUIRED	4
PREPARE & TEST THE DOOR	4
DOOR REQUIREMENTS	5
ASSEMBLY	6
INSTALLATION	7-10
CONNECT ELECTRIC POWER	10
INSTALL MULTI-FUNCTION DOOR	

CONTROL	10
INSTALL THE PROTECTOR SYSTEM	11
AUTO CLOSE	13
ADJUSTMENT	14-17
WIRELESS PROGRAMMING	18-19
REPAIR PARTS	20
DIAGNOSTIC CHART	21
TROUBLESHOOTING	22
CARE OF YOUR OPENER	23
OPERATION OF YOUR OPENER	23
WARRANTY	24

CARTON INVENTORY

Your door opener is packaged in one carton which contains the opener and the parts illustrated below. Note that accessories will depend on the model purchased. If anything is missing, carefully check the packing material.



Hardware Inventory


INSTALLATION HARDWARE

- Hex Screw #14-10x1-7/8" (4)
- Screw #6x-1" (2)
- Hex Screw #6x1-1/4" (2)
- Carriage Bolt 1/4"-20x1/2" (2)
- Pan Head Screw 1/4"-20x1/2" (2)
- Hex Head Screw #8x1" (2)
- Self Tapping Screw #10-32 (2)
- Wall Anchor (2)
- Wall Anchor (Screw-In) (2)
- Handle
- Rope
- Insulated Staples (10)
- Lock Template

PROTECTOR SYSTEM™ (IR) INSTALLATION HARDWARE

- Screw 10-32x3/8" (4)
- Carriage Bolt 1/4"-20x1/2" (4)
- Wing Nut 1/4"-20 (2)
- Hex Nut 10-32x3/8" (4)
- Hex Nut 1/4-20 (4)
- Hex Head Screw 1/4-20x1-1/2" (2)
- Hex Head Screw 14-10 x 1-1/2" (4)
- Insulated Staple (10)

ACCESSORIES



NOTE: Only genuine Merlin accessories are approved for use with this opener. Generic compatible accessories are **NOT** approved for use with this opener.

(1) Model E960M	4 Channel Premium remote control	(6) Model C840	Keyless Entry System
(2) Model CM128	Wireless Wall Button	(7) Model 774ANZ	The Protector System™
(3) Model C940	1 Channel visor remote control	(8) Model 760E	Outside Keyswitch
(4) Model C943	3 Channel visor remote control	(9) Model CM475	Battery Backup
(5) Model C945	3 Channel mini remote control		

PREPARING YOUR DOOR

Before you begin:

- Disable locks.
- Remove any ropes connected to door.
- **Complete the following test** to make sure your door is balanced and is not sticking or binding:
 1. Lift the door about halfway as shown. Release the door. If balanced, it should stay in place, supported entirely by its springs.
 2. Raise and lower the door to see if there is any binding or sticking, 20 kgf is the absolute maximum allowable force to raise or lower the door in any position.

IF YOUR DOOR BINDS, STICKS OR IS OUT OF BALANCE, CALL A TRAINED DOOR SYSTEMS TECHNICIAN.


3. Verify equal cable tension on each side of door. Cable tension should remain equal during the entire travel of the door.



Sectional Door

Tools needed

During assembly, installation and adjustment of the opener, instructions will call for hand tools as illustrated below.



Please note this opener contains both imperial and metric fasteners.

⚠ WARNING

To prevent possible **SERIOUS INJURY** or **DEATH**:

- **ALWAYS** call a trained door systems technician if door binds, sticks or is out of balance. An unbalanced door may not reverse when required.
- **NEVER** try to loosen, move or adjust door, door springs, cables, pulleys, brackets or their hardware, ALL of which are under **EXTREME** tension.
- Disable **ALL** locks and remove **ALL** ropes connected to the door **BEFORE** installing and operating the door opener to avoid entanglement.
- This device is not intended for use by small children or infirmed persons without supervision.
- young children should **NOT** be permitted to play with the opener or transmitters.

CAUTION

To prevent damage to door and opener:

- **ALWAYS** disable locks **BEFORE** installing and operating the opener.

Specifications

Volts: 230-240 ~ V 50 Hz

Power: 145 Watts

Rated Load: 10Nm

Fmax: 40Nm

Max door height: up to 4.2 m (with max. door area 16.5m²)

Max door width: up to 5.5 m (with max. door area 16.5m²)

Max door area: 16.5 m²

Max door weight: 130 kg

Max lift under spring tension: 20 kg

DOOR REQUIREMENTS

Survey the area to see if any of the conditions below apply to your installation. Additional materials may be required. You may find it helpful to refer back to this page as you proceed with the installation of your opener.


Depending on your requirements, there are several installation steps which may call for materials or hardware not included in the carton.

This opener is compatible with:

- Doors that use a torsion bar, springs and a door no more than 4.2m high.
- 100mm - 150mm drums , **NOT TO BE USED** on tapered drums over 150mm .
- High lift and standard lift sectional doors up to 4.2m high.
- Doors up to 5.5m wide.
- Doors up to 16.5m² (max. door area)
- 25mm torsion bar only.
- Review or inspect proposed installation area. Opener can be installed on left or right side of door. Select the side that meets the requirements listed below.
- Must have minimum of 64mm between the wall and the center of the torsion bar.
- Must have minimum of 76mm between the ceiling and the center of torsion bar.

- Must have minimum of 203mm between the side wall (or obstruction) and the end of torsion bar.
- The torsion bar must extend at least 25mm to 100mm past the bearing plate.
- An electric outlet is required within 1.8m of the installation area. If outlet does not exist, contact a qualified electrician.
- Depending upon building's construction, extension brackets or wood blocks may be needed to install safety reversing sensors.
- A model CM475 EverCharge™ Battery Backup Unit (BBU) is strongly recommended if there is no access door to the building, as this opener cannot be used in conjunction with an external emergency release mechanism.
- Any gap between the floor and the bottom of the door must not exceed 6mm. Otherwise the safety reversal system may not work properly.

NOTE: Inspect the torsion bar while the door is raised and lowered. It is important that there is no noticeable movement up and down or left and right. If this type of movement is not corrected, life of this opener will be greatly reduced.



ASSEMBLY STEP 1

Attach the Collar to the Opener

To avoid installation difficulties, do not run the door opener until instructed to do so.

- Loosen the collar screws.
- Attach collar to either the left or the right side of the opener. Depending on Left or Right hand installation ensure that the collar is seated all the way on motor shaft until stop is reached (Figure 1).
- Position the collar so that the screws are accessible when attached to the torsion bar.
- Tighten both sides of collar screws equally (Figure 2) to secure collar to the opener (16Nm-19Nm of torque).
- Do not tighten set screws as yet.

NOTE: Nylon Patch has been added to the collar screws, so it is normal for some thread resistance to be evident.

⚠ WARNING

To prevent possible **SERIOUS INJURY** or **DEATH**, the collar **MUST** be properly tightened. The door may not reverse correctly or limits may be lost due to collar slip.




Figure 1





Figure 2

ASSEMBLY STEP 2


Attach Mounting Bracket to Opener

- Loosely attach slotted side of mounting bracket to the same side of the opener as the collar, using self-threading screws provided.


NOTE: Do not tighten until instructed. Illustrations shown are for left side installation.



Alternate Mounting Kit (NOT SUPPLIED):



This kit allows model MJ3800 to be mounted below the torsion bar in the case where the torsion bar is not round or the normal mounting area is obstructed.



INSTALLATION

IMPORTANT INSTALLATION INSTRUCTIONS

WARNING

To reduce the risk of **SEVERE INJURY** or **DEATH**:

1. READ AND FOLLOW ALL INSTALLATION WARNINGS AND INSTRUCTIONS.
2. Install door opener ONLY on properly balanced and lubricated the door. An improperly balanced door may not reverse when required and could result in SEVERE INJURY or DEATH.
3. ALL repairs to cables, spring assemblies and other hardware MUST be made by a trained door systems technician BEFORE installing opener.
4. Disable ALL locks and remove ALL ropes connected to the door BEFORE installing opener to avoid entanglement.
5. Mount emergency release handle no higher than 1.8m above floor.
6. NEVER connect the door opener to power source until instructed to do so.
7. NEVER wear watches, rings or loose clothing while installing or servicing opener. They could be caught in the door or opener mechanisms.
8. Install wall-mounted door control:
 - within sight of the door.
 - out of reach of children at minimum height of 1.5 m.
 - away from ALL moving parts of the door.
9. Place entrapment warning label on wall next to multi function door control.
10. Place manual release/safety reverse test label in plain view on inside of the door.
11. Upon completion of installation, test safety reversal system. Door MUST reverse on contact with a 40mm (1 1/2") high obstacle placed on the floor.

INSTALLATION STEP 1

Position the Opener

1. Close the door completely.
2. Slide the opener with collar over the end of the torsion bar. Ensure that the collar does not touch the bearing plate. Check to make sure the mounting bracket is located on a solid surface such as wood, concrete or door/flag bracket. Snug collar screws to help assure proper alignment of opener. Mark the bracket holes. It may be necessary to cut the torsion bar if it is too long or damaged.
3. Loosen collar screws from torsion bar and remove the opener. Drill 5mm (3/16") pilot holes at the marked locations. Drill through steel plate if needed.
4. Reinstall the opener by sliding the collar over the torsion bar until pilot holes align with bracket. Securely tighten collar screws that attach to the torsion bar to 16Nm-19Nm of torque. Securely tighten both set screws firmly, without damaging the opener.
5. Fasten bracket securely with 14-10x1-7/8" screws. Tighten all mounting bracket hardware.


NOTE: The opener does not have to be flush to wall, but it is essential it is mounted perfectly square to the torsion bar. This will ensure smooth operation with minimum stress at the connecting collar mount.

6. Use a staple to secure the antenna wire to prevent antenna from being entangled in a door roller.

WARNING

To prevent possible **SERIOUS INJURY** or **DEATH**:

- Concrete anchors **MUST** be used if mounting bracket into masonry.
- **NEVER** try to loosen, move or adjust the door, springs, cables, pulleys, brackets or their hardware, **ALL** of which are under **EXTREME** tension.
- **ALWAYS** call a trained door systems technician if the door binds, sticks or is out of balance. An unbalanced door might not reverse when required.
- Opener **MUST** be mounted at a right angle to the torsion bar to avoid premature wear on the collar.



INSTALLATION STEP 2

Attach the Emergency Release Rope and Handle

- Thread one end of the rope through the hole in the top of the red handle so "NOTICE" reads right side up as shown. Secure with an overhand knot at least 25mm (1") from the end of the rope to prevent slipping.
- Thread the other end of the rope through the loop in the emergency release cable.
- Adjust rope length so the handle is no higher than 1.8m (6') above the floor. Secure with an overhand knot.

NOTE: If it is necessary to cut the rope, heat seal the cut end to prevent unraveling.


INSTALLATION STEP 3

Install powered door lock

The lock is used to prevent the door from being manually opened once the door is fully closed.

1. Select a door roller to mount the lock above. Check for clearance. If possible select a roller on the same side of the door as the opener. The second roller up from the bottom is ideal in most installations.
2. Ensure the door track surface is clean and adhere lock template with bottom edge just above the highest point on the roller (Figure 1).
3. Drill holes as marked on the template.
4. Fasten powered door lock to the outside of the door track with hardware provided.
5. Run bell wire up wall to opener. Use insulated staples to secure wire in several places.
6. Plug connector into the opener (Figure 2).

NOTE: Lock must be mounted within 3m (10') of the power head.



⚠ WARNING

To prevent possible **SERIOUS INJURY** or **DEATH** from a falling door:

- If possible, use emergency release handle to disengage door **ONLY** when door is **CLOSED**. Weak or broken springs or unbalanced door could result in an open door falling rapidly and/or unexpectedly.
- **NEVER** use emergency release handle unless the doorway is clear of persons and obstructions.





Figure 1




Figure 2

INSTALLATION STEP 4

Attach the Cable Tension Monitor (Required)

Your MJ3800 is supplied with a cable tension monitor. This safety device is supplied to monitor the cable for ANY slack that may occur and will reverse the door when excessive slack is detected, eliminating service calls.

The cable tension monitor **MUST** be connected and properly installed before the door opener will move in the down direction.

NOTE: The cable tension monitor is shipped for left side installation. It is preferred that the cable tension monitor be installed on the same side of the door as the opener.

If required, it can be mounted on the opposite side of door. Remove the snap-ring holding the roller in place and reassemble it on the opposite side of the cable tension monitor.

1. Position the cable tension monitor as shown (Figures 1 and 2). The cable tension monitor should be located as close to the drum as possible.

NOTE: There must be no obstructions in the installation area that prevent the cable tension monitor or the cable itself from closing completely when slack is detected.

2. Make sure cable tension monitor is located over a wood support member.

NOTE: If the cable tension monitor can not be mounted into wood with the lag screws provided, it can be mounted into 25mm (1") or greater pasterboard using the wall anchors (2) and the #8 hex head screws (2) provided in the hardware bag.

3. Mark and drill 5mm (3/16") pilot holes for screws (pilot holes are not required for anchors).
4. Attach the cable tension monitor to the wall using the hardware provided. Make sure that the roller is on top of the cable.
5. Run bell wire to opener. Use insulated staples to secure wire in several places.
6. Connect bell wire to the green quick-connect terminals (polarity is not important) (Figure 3).

NOTE: Cable must have tension through entire travel. Make sure there is no slack in cable on opposite side of the door during normal operation. If this condition exists, adjust cables as required.




Figure 1




Figure 2





Figure 3



WARNING

To prevent possible SERIOUS INJURY or DEATH from electrocution or fire:

- Be sure power is not connected to the opener, and disconnect power to circuit BEFORE removing cover.
- Door installation and wiring MUST be in compliance with ALL local electrical and building codes.
- NEVER use an extension cord, 2-wire adapter or alter the plug in any way to make it fit outlet. Be sure the opener is grounded.
- If the supply cord is damaged, it must be replaced by the manufacturer or it's service agent or a similiarly qualified person in order to avoid harzard.

INSTALLATION STEP 5

INSTALLING THE MULTI-FUNCTION WALL CONTROL

Note: any connection to your MJ3800 should be voltage free and Normally open.

There are 2 screw terminals on the back of the multi-function door control. Strip about 6mm of insulation from bell wire. Separate wires enough to connect the white/red wire to R terminal screw 1 and the white wire to W terminal screw 2.

Fasten the multi-function door control to an inside garage wall with sheet metal screws provided. Drill 4mm holes and use anchors if installing into plasterboard wall. A convenient place is beside the service door and out of reach of children.

Run the bell wire up the wall and across the ceiling to the garage door opener. Use insulated staples to secure wire. The receiver quick connect terminals are located on the control board. Connect the bell wire to the terminals as follows: white/red to red and white to white.

INSTALLATION STEP 6

Installing the Wireless Wall button (CM128)

Control must be mounted out of the reach of children at a height of 1.5m with an unobstructed view of the door.

- Ensure your MJ3800 opener is switched off whilst installing your wireless door control to prevent accidental activation.
- Remove the cover from the CM128.
- Mount CM128 as shown using the screws provided if mounting into a wall box (not provided).
- If mounting directly on the wall use wall anchors (provided) to fix unit to the plasterboard wall.
- Replace the cover plate and **affix the warning label adjacent the wall controller.**


Fix the emergency door release label adjacent to the opener.

NOTE: The wireless wall button supplied with your opener should be preprogrammed by the factory. If adding a new wireless wall button, program into the opener before mounting the unit.

WARNING


To prevent possible SERIOUS INJURY or DEATH from a falling door:

- If possible, use emergency release handle to disengage door ONLY when door is CLOSED. Weak or broken springs or unbalanced door could result in an open door falling rapidly and/or unexpectedly.
- NEVER use emergency release handle unless the doorway is clear of persons and obstructions.



WARNING

Disconnect power to the opener whilst installing this accessory to prevent accidental activation. Locate minimum 1.5m above the floor.



INSTALLATION STEP 7

Install The Protector System™



When installed the safety reversing sensor **must** be connected and aligned correctly before the door opener will move in the down direction. This safety device is provided for your safety and should not be disabled.

NOTE: The speed will also be increased by $\frac{1}{3}$ in the down direction.


INSTALLING THE BRACKETS

Be sure power to the opener is disconnected.

Figures 1, 2 and 3 show recommended assembly of bracket(s) and "C" wrap based on the *wall* installation of the sensors on each side of the door shown above, or on the *door tracks* themselves. Figures 4, 5 & 6 show variations which may fit your installation requirements better. **Make sure the wraps and brackets are aligned so the sensors will face each other across the door.**

- Connect each assembly to a slotted bracket, using the hardware shown. **Note alignment of brackets for left and right sides of the door.** Finger tighten the lock nuts.
 - Use bracket mounting holes as a template to locate and drill (2) (4.8mm) diameter pilot holes on both sides of the door, (100mm). Max height is (100mm).
 - Attach bracket assemblies with 1/4"x1-1/2" lag screws as shown.
 - Adjust right and left side bracket assemblies to the same distance out from mounting surface. Make sure all door hardware obstructions are cleared. Tighten the nuts securely.
 - Centre each sensor unit in a "C" wrap with lenses pointing toward each other across the door.
 - Secure sensors with the hardware shown in Figure 6. Finger tighten the wing nut on the *receiving eye* to allow for final adjustment. Securely tighten the *sending eye* wing nut.
 - Run wires from both sensors to the opener as shown on Page 12. Use insulated staples to secure the wire to the wall and ceiling.
 - Connect both sets of wires to the opener terminals as shown page 12.
 - Plug in the opener. If your opener has the Multi-Function Door Control, make sure the Lock Feature is *off*. Red indicator lights in both the sending and receiving eyes will *glow* if wiring connections and alignment are correct.
- If the indicator lights are *flashing* (and the invisible light beam path is not obstructed), alignment is required.
- Loosen the receiving eye wing nut to allow slight rotation of unit. Adjust sensor vertically and/or horizontally until the red indicator light *glows*.
 - When indicator lights are glowing in both units, tighten the wing nut in the receiving eye unit.

figure 1



⚠ WARNING

Be sure power is not connected to the door opener BEFORE installing the safety reversing sensor.

To prevent SERIOUS INJURY or DEATH from a closing door:

- Correctly connect and align the safety reversing sensor. This required safety device **MUST NOT** be disabled.
- Install the safety reversing sensor so beam is **NO HIGHER** than 100mm (4") above the floor.




figure 2




figure 3




figure 4




figure 5




figure 6

WARNING

CONNECT ELECTRIC POWER

TO AVOID INSTALLATION DIFFICULTIES, DO NOT RUN THE GARAGE DOOR OPENER UNTIL INSTRUCTED TO DO SO.


Connect to properly fused and earth power outlet.

INSTALLATION STEP 8

Mounting the Evercharge Battery Backup Unit (BBU)

If the CM475 Standby power supply unit is part of this installation it should be installed at this time.

- The BBU can be mounted to either the ceiling or a wall within 3' (.9 m) of the opener.
- Position the BBU as desired to a structural support (ceiling joist or wall stud).
- Attach the BBU to the support using the mounting holes on either side of the BBU.
- Secure the BBU using the 1-1/2" lag screws (2) provided with the BBU unit.
- Connect the BBU cord into the connector on the bottom of the opener.
- Follow all instructions included with the CM475 unit to test for proper operation and testing of the BBU.



USING THE MULTI-FUNCTION DOOR CONTROL

THE MULTI-FUNCTION DOOR CONTROL

Press the push bar to open or close the door. Press again to reverse the door during the closing cycle or to stop the door while it's opening.

Light feature



The Light function is not available with the MJ3800.


Lock feature



Designed to prevent operation of the door from hand-held transmitters whilst still allowing the door to open and close from the Door Control, the Outdoor Key Switch and the Keyless Entry Accessories. To activate, press and hold the Lock button for 2 seconds.

To turn off, press and hold the Lock button again for 2 seconds. The Lock feature will also turn off whenever the "learn" button on the opener panel is activated.

Note: This feature does not operate the Powered door lock.



AUTOMATIC CLOSE TIMER FUNCTION

Note: Requires the Chamberlain Protector System™ (IR-sensors) to be installed. If Protector System™ (IR-sensors) is installed to enable the timer to close function (first time), install sensors, close the garage door and wait for 5 minutes. A Multi-function Door Control is required to enable and disable the auto-close function.

Enable: Push and hold lock button on the Multi-function Door Control until the electric lock toggled twice. Release the lock button, at the same time watch the LED light in the center of the actuator button from the Multi-function Door Control.

1x flash 10 seconds Auto-Close

2x flash 45 seconds Auto-Close

3x flash 2 minutes Auto-Close

4x flash 3 minutes Auto-Close

5x flash OFF Auto-Close

Factory setting is OFF. Repeat the procedure until the Multi-function Door Control shows the required number of flashes.

⚠ WARNING

Auto close is NOT recommended for households with young children.

⚠ WARNING

Door may operate unexpectedly, therefore do not allow anything to stay in the path of the door.

TROUBLESHOOTING THE SAFETY REVERSING SENSORS

1. If the *sending eye* indicator LEDs are both flashing after installation, check for:


- Electric power to the opener.
- A short in the white or white/black wires. These can occur at staples, or at opener connections.
- Incorrect wiring between safety reversing sensors and opener.
- A broken wire.

2. If the sending eye indicator light *glows steadily* but the receiving eye indicator light doesn't:

- Check alignment.
- Check for an open wire to the *receiving eye*.

3. If the *receiving eye* indicator light is dim, realign either sensor.

NOTE: When the invisible beam path is obstructed or misaligned while the door is closing, the door will reverse. If the door is already open, it will not close and the LED indicator light will flash 10 times. See page 21.




ADJUSTMENT STEP 1

Program the Travel Limits

Travel limits regulate the points at which the door will stop when moving up or down. Follow the steps below to set the limits.

Figure 1



To program the travel limits:

Adjust the position of the door by using the black and orange buttons. Black moves the door UP (open) and orange moves the door DOWN (close).

1. **Setting the UP position:** Press and hold the black button until the yellow indicator light starts flashing slowly then release.
2. Push and hold the black button until the door reaches the desired UP (open) position (Figure 2).

NOTE: Check to be sure the door opens high enough for your vehicle to pass under.

3. Push the transmitter, wireless wall button or multi-function door control (Figure 3). This sets the UP (open) limit and begins closing the door.

NOTE: Excessive movement of the opener will cause premature wear. See Troubleshooting section.

4. Immediately when the door begins to move down, press and release either the black or orange button. This will stop the door.
5. **Setting the DOWN position:** Push and hold the orange button until the door reaches the desired DOWN (closed) position (Figure 4).
6. Once the door is closed, check for proper pressure on the door (you should be able to manually push the door down 2mm). If there appears to be too much pressure on the door, you may toggle the door back and forth using the black and orange buttons to reach the desired position.
7. Push the transmitter, wireless wall button or the multi-function door control (Figure 3). This sets the DOWN (close) limit and should bring the door to the open position.

- If the opener is not stopping exactly where you would like it, repeat steps 1 through 7 and program the limits again.
- When the unit stops in both the desired up (open) and down (close) positions, proceed to *Adjustment Step 2, Setting the Force.*

⚠ WARNING

Without a properly installed safety reversal system, persons (particularly children) could be **SERIOUSLY INJURED** or **KILLED** by a closing door.

- NEVER learn forces or limits when door is binding or sticking. Repair door first.
- Incorrect adjustment of the door travel limits will interfere with proper operation of safety reversal system.
- After ANY adjustments are made, the safety reversal system **MUST** be tested. Door **MUST** reverse on contact with 40mm high (1 1/2") object on floor.

CAUTION

To prevent damage to vehicles, be sure fully open door provides adequate clearance.

Figure 2




Figure 3





Figure 4



ADJUSTMENT STEP 2

Setting the Force

The force setting button is located on the front panel. The force setting measures the amount of force required to open and close the door.

1. Locate the orange button on the unit (Figure 1).
2. Push the orange button twice to enter unit into Force Adjustment Mode (Figure 2). The LED (Indicator Light) will flash quickly.
3. Push the transmitter, wireless wall button or multi-function door control (Figure 3). The door will travel to the DOWN (close) position. Push the transmitter, wireless wall button or multi-function door control again, the door will travel to the UP (open) position. Push the transmitter, wireless wall button or multi-function door control a third time to send the door to the DOWN (close) position.

The LED (Indicator Light) will stop flashing when the force has been learnt.




The unit has learnt the forces required to open and close your door.

The door must travel through a complete cycle, UP and DOWN, in order for the force to be set properly. If the unit cannot open and close your door fully, inspect your door to ensure that it is balanced properly and is not sticking or binding. See page 4, "Preparing your door."

WARNING

Without a properly installed safety reversal system, persons (particularly children) could be SERIOUSLY INJURED or KILLED by a closing the door.

- NEVER learn forces or limits when door is binding or sticking. Repair door first
- Too much force on door will interfere with proper operation of safety reversal system.
- After ANY adjustments are made, the safety reversal system MUST be tested. Door MUST reverse on contact with 40mm (1 1/2") high obstacle on floor.



ADJUSTMENT STEP 3

Test Cable Tension Monitor

If your cable tension monitor has been activated the unit will not close (the LED will flash 9 times). See (Figure 1) page 9.

ADJUSTMENT STEP 4

Test Powered Door Lock

TEST


- With the door fully closed, the powered door lock bolt should be protruding through the track.
- Operate the door in the open direction. The powered door lock should retract before the door begins to move.
- Operate the door in the down direction. When the door reaches the fully closed position, the powered door lock should automatically activate to secure the door.

NOTE: If the powered door lock does not function, the lock can be manually released by sliding the manual release handle to the open position.

⚠ WARNING

Without a properly installed safety reversal system, persons (particularly children) could be **SERIOUSLY INJURED** or **KILLED** by a closing the door.

- Safety reversal system **MUST** be tested every month.
- If one control (force or travel limits) is adjusted, the other control may also need adjustment.
- After **ANY** adjustments are made, the safety reversal system **MUST** be tested. Door **MUST** reverse on contact with 40mm (1 1/2") high obstacle on the floor.



⚠ WARNING

Without a properly installed safety reversing sensor, persons (particularly children) could be **SERIOUSLY INJURED** or **KILLED** by a closing door.



ADJUSTMENT STEP 5

Test the Safety Reversal System

TEST

- With the door fully open, place a 40mm (1 1/2") obstacle on the floor, centered under the the door.
- Operate the door in the down direction. The door **must** reverse on contact with the obstruction. Upon successful safety reversal test proceed to "Adjustment Step 6".

ADJUST

- If the door stops on the obstruction, it is not traveling far enough in the down direction. Complete Adjustment Steps 1 and 2 Programming the Limits and Forces.
- Repeat the test.
- When the door reverses on the 40mm (1 1/2") obstacle, remove the obstruction and run the opener through 3 or 4 complete travel cycles to test adjustment.
- If the unit continues to fail the Safety Reverse Test, call for a trained door systems technician.

IMPORTANT SAFETY CHECK:

Test the Safety Reverse System after:

- Each adjustment of limits, or force controls.
- Any repair to or adjustment of the door (including springs and hardware).
- Any repair to or buckling of the floor.
- Any repair to or adjustment of the opener.


ADJUSTMENT STEP 6

Test The Protector System®

- Press the transmitter push button to open the door.
- Place the opener carton in the path of the door.
- Press the transmitter push button to close the door. The door will not move and the LED indicator light will flash twice.

The door opener will not close from a transmitter if the indicator light in either sensor is flashing or off (alerting you to the fact that the sensor is misaligned or obstructed).

If the opener closes the door when the safety reversing sensor is obstructed, do not operate the door. Call for a trained door systems technician.



OPERATION

IMPORTANT SAFETY INSTRUCTIONS

WARNING

To reduce the risk of SEVERE INJURY or DEATH:

1. READ AND FOLLOW ALL WARNINGS AND INSTRUCTIONS.
2. ALWAYS keep transmitters out of reach of children. NEVER permit children to operate or play with the wireless wall button, multi-function door control or transmitters.
3. ONLY activate the door when it can be seen clearly, it is properly adjusted and there are no obstructions to door travel.
4. ALWAYS keep the door in sight until completely closed. NO ONE SHOULD CROSS THE PATH OF THE MOVING DOOR.
5. NO ONE SHOULD GO UNDER A STOPPED, PARTIALLY OPENED DOOR.
6. If possible, use emergency release handle to disengage door ONLY when the door is CLOSED. Weak or broken springs or unbalanced door could result in an open door falling rapidly and/or unexpectedly.
7. NEVER use emergency release handle unless the doorway is clear of persons and obstructions.
8. After ANY adjustments are made, the safety reversal system MUST be tested.
9. Safety reversal system MUST be tested every month. The door MUST reverse on contact with 40mm (1 1/2") high obstacle on the floor.
10. ALWAYS KEEP THE DOOR PROPERLY BALANCED (see page 3). An improperly balanced door may not reverse when required and could result in SEVERE INJURY or DEATH.
11. ALL repairs to cables, spring assemblies and other hardware, ALL of which are under EXTREME tension, MUST be made by a trained door systems technician.
12. ALWAYS disconnect electric power to the door opener BEFORE making ANY repairs or removing covers.
13. Permanently fix the Emergency release instruction Label adjacent to the release handle.
14. **SAVE THESE INSTRUCTIONS.**

EMERGENCY DOOR RELEASE

WARNING

To prevent possible SERIOUS INJURY or DEATH from a falling door:

- If possible, use emergency release handle to disengage door ONLY when door is CLOSED. Weak or broken springs or unbalanced door could result in an open door falling rapidly and/or unexpectedly.
- NEVER use emergency release handle unless the doorway is clear of persons and obstructions.

WARNING


ADJUSTMENT STEP 7

To Open the Door Manually

Disengage door lock before proceeding. The door should be fully closed if possible. Pull down on the emergency release handle until a click noise is heard from the unit and lift the door manually. To reconnect the door to the opener, pull down the emergency release handle straight down a second time until a click noise is heard from the unit. The door will reconnect on the next UP or DOWN operation.

Test the emergency release:

- Make sure the door is closed.
- Pull the emergency release handle. The door should then be able to be opened manually.
- Return the door to the closed position.
- Pull the emergency handle a second time.
- Reconnect the door to the opener.




WIRELESS PROGRAMMING

Your door opener has already been programmed at the factory to operate with your hand-held transmitter. The door will open and close when you press the large centre button.


Below are instructions for programming your opener to operate with additional Security+ transmitters.

To Add or Reprogram a Hand-held Transmitter


USING THE "LEARN" BUTTON





1. Press and hold button you wish to program to the opener.



2. The orange LED (indicator light) will flash to indicate it is receiving signal from the transmitter.



3. Press and release the orange button. The LED turns off (approx. 2 sec).



To Erase All Codes From Opener Memory

To deactivate any unwanted transmitter, first erase all codes: Press and hold the orange "learn" button on opener until the learn indicator LED goes out (approximately 6-9 seconds).

Note: All previous codes are now erased.

Reprogram each transmitter or keyless entry you wish to use.

3-Button Transmitters

If provided with your garage door opener, the large button is factory programmed to operate it. Additional buttons on any 3-button transmitter or mini-transmitter can be programmed to operate other Merlin Professional garage door openers or gate openers.








Figure 1

TO ADD, REPROGRAM OR CHANGE A KEYLESS ENTRY PIN

USING THE "LEARN" BUTTON

1. Press and release the orange "learn" button on opener. The learn indicator LED will glow steadily for 30 seconds.
2. Within 30 seconds, enter a four digit personal identification number (PIN) of your choice on the keypad. Then press and hold the ENTER button.
3. Release the button when the opener LED turns off.



To change an existing, known PIN

If the existing PIN is known.

1. Press the four buttons for the present PIN, then press and hold the # button.
The LED on the opener will turn on.

2. Press the new 4-digit PIN you have chosen, then press Enter.

The indicator LED will turn off. Code has been learnt.

Test by pressing the new PIN, then press Enter. The door should move.

To set a temporary PIN

You may authorise access to visitors or service people with a temporary 4-digit PIN. After a programmed number of hours or number of accesses, this temporary PIN expires and will no longer open the door. It can be used to *close* the door even after it has expired. To set a temporary PIN:

1. Press the four buttons for your personal entry PIN (not the last temporary PIN), then press and hold the * (star button).
2. Press the temporary 4-digit PIN you have chosen, then press Enter.
3. To set the number of **hours** this temporary PIN will work, press the number of hours (up to 255), then press * (star button).

OR

3. To set the number of **times** this temporary PIN will open door, press the number of times (up to 255), then press # (hash button).

The indicator light will turn off when the temporary PIN has been learnt.

Test by pressing the four buttons for the temporary PIN, then press Enter. The door should move. If the temporary PIN was set to a certain number of openings, remember that the test has used up one opening. To clear the temporary password, repeat steps 1-3, setting the number of hours or times to 0 in step 3.

One Button Close: Opener can be closed by pressing only the ENTER button if the one button close feature has been activated. This feature has been activated at the factory. To activate or deactivate this feature press and hold buttons 1 and 9 for 10 seconds. The keypad will flash twice when the one button close is active. The keypad will flash four times when one button close is deactivated.

The Transmitter Battery

! WARNING

To prevent possible **SERIOUS INJURY** or **DEATH**:

- NEVER allow small children near batteries.
- If battery is swallowed, immediately notify doctor.



! WARNING

To reduce risk of fire, explosion or chemical burn:


- Replace **ONLY** CR2032 batteries.
- Do **NOT** recharge, disassemble, heat above 75°C or incinerate.

To replace battery, use a screwdriver blade to pry open the case as shown. Insert battery positive side up.

Dispose of old battery properly.






REPAIR PARTS



KEY NO.	PART NO.	DESCRIPTION™			
1	041A6102-1	Electric powered door lock			
2	CM128	Wireless wall button			
3	C77	Protector system™ (IR Beams)			
4	041A6388	Collar with set screws			
5	C945	3ch rolling code transmitter			
			6	041A4582	Emergency release rope & handle assembly
				041B4494-1	2-Conductor bell wire - white & white/red
			7	041A6104-1	Cable tension monitor
			8	041C0902	Mounting bracket

Opener Assembly Parts





Your door opener is programmed with self-diagnostic capabilities. The "Learn" button/diagnostic LED will flash a number of times then pause signifying it has found a potential issue. Consult Diagnostic Chart below.

Diagnostic Chart

1 FLASH

Safety reversing sensors wire open (broken or disconnected).

OR

2 FLASHES

Safety reversing sensors wire shorted or black/white wire reversed.

3 FLASHES

multi-function door control or wire shorted.

4 FLASHES

Safety reversing sensors slightly misaligned (dim or flashing LED).

5 FLASHES

Possible RPM sensor failure. Unplug to reset.

9 FLASHES

Cable tension monitor reversal.

- **Symptom: One or both of the Indicator lights on the safety reversing sensors do not glow steady.**
 - Inspect sensor wires for a short (staple in wire), correct wiring polarity (black/white wires reversed), broken or disconnected wires, replace/attach as needed.
 - Disconnect all wires from opener.
 - Remove sensors from brackets and shorten sensor wires to 30-60mm (1-2") from back each of sensor.
 - Reattach sending eye to opener using shortened wires. If sending eye indicator light glows steadily, attach the receiving eye.
 - Align sensors, if the indicator lights glow replace the wires for the sensors. If the sensor indicator lights do not light, replace the safety reversing sensors.
- **Symptom: LED is not lit on multi-function door control.**
 - Inspect Multi-Function Door Control/wires for a short (staple in wire), replace as needed.
 - Disconnect wires at multi-function door control, touch wires together. If opener activates, replace multi-function door control.
 - If opener does not activate, disconnect multi-function door control wires from opener. Momentarily short across red and white terminals with jumper wire. If opener activates, replace multi-function door control wires.
- **Symptom: Sending indicator light glows steadily, receiving indicator light is dim or flashing.**
 - Realign receiving eye sensor, clean lens and secure brackets.
 - Verify door track is firmly secured to wall and does not move.
- **Symptom: The RPM Sensor = Short travel 150-200mm (6-8").**
 - Unplug unit to reset. Try to operate opener, check diagnostic code.
 - If it is still flashing 5 times and opener moves 150-200mm (6-8"), the unit's APE (Absolute Positioning Encoder) may need to be replaced, for details contact your Chamberlain reseller.
- **Symptom: Door reverses while closing.**
 - Check for possible door obstructions and remove.
 - Check that the cable tension monitor is properly connected to the opener.
 - Replace the cable tension monitor.

TROUBLESHOOTING

1. The opener doesn't operate from either the multi-function door control, wireless wall button or the transmitter:

- Does the opener have electric power? Plug a lamp into the outlet. If it doesn't light, check the fuse box or the circuit breaker. (Some outlets are controlled by a wall switch.)
- Have you disabled all door locks? Review installation instruction warnings on page 7.
- Is there a build-up of ice or snow under the door? The door may be frozen to the ground. Remove any restriction.
- The door spring may be broken. Have it replaced (see page 5 for reference).

2. Opener operates from the transmitter, but not from the Wireless Wall Button:

- Check the LED on the Wireless Wall Button to ensure the LED turns on when button is pushed. If the LED is weak or not on Change the batteries. (Remove cover and replace with CR2032 batteries X 2)
- If the LED turns on and is strong check to ensure the unit is programmed into the unit (see page 19).

3. The door operates from the multi-function door control but not from the transmitter:

- Is the door push bar flashing? If so, Lock mode is engaged. Make sure it is off by pressing the Lock button for two seconds.
- Program the opener to match the transmitter code. (Refer to instructions on the opener panel.) Repeat with all Transmitter.

4. The transmitter has short range:

- Change the location of the transmitter in your car.
- Check to be sure the antenna on the side or back panel of opener extends fully downward.
- Some installations may have shorter range due to a metal door, foil backed insulation, or metal siding.

5. The door opens and closes by itself:

- Be sure that all transmitter push buttons are off.
- Remove the bell wire from the multi-function door control terminals and operate from the transmitter only. If this solves the problem, the multi-function door control is faulty (replace), or there is an intermittent short on the wire between the control console and the opener.
- Clear memory and re-program all transmitters.

6. The door doesn't open completely:

- Check powered door lock.
- Is something obstructing the door? Is it out of balance, or are the springs broken? Remove the obstruction or repair the door.

7. The door opens but won't close:

- Check cable tension monitor (see installation step 4).
- If the opener LED is flashing, check the safety reversing sensor. See *Installation Step 8*.
- If the opener LED is not flashing and it is a new installation. See *Adjustment Step 2*. For an existing installation, see below.

Repeat the safety reverse test after the adjustment is complete.

8. The door reverses for no apparent reason and opener LED doesn't flash:

- Check cable tension monitor (see installation step 4).
- Is something obstructing the door? Pull the emergency release handle. Operate the door manually. If it is unbalanced or binding, call a trained door systems technician.
- Clear any ice or snow from the floor area where the door closes.
- Review *Adjustment Step 2*.

Repeat safety reverse test after adjustments.

9. The door reverses for no apparent reason and opener LED flashes for 5 seconds after reversing:

- Check the safety reversing sensor. Remove any obstruction or align the receiving eye. See *Installation Step 8*.

10. The opener strains to operate door:

- The door may be out of balance or the springs may be broken. **Close the door** and use the emergency release handle to disconnect the door. Open and close the door manually. A properly balanced door will stay in any point of travel while being supported entirely by its springs. If it does not, disconnect the opener and call a trained door systems technician.

11. The opener motor hums briefly, then won't work:

- The door springs may be broken. See above.
- If the problem occurs on the first operation of the opener, door may be locked. Disable the powered door lock.

12. The opener won't operate due to power failure:

- Manually open the powered door lock.
- Use the emergency release handle to disconnect the door. The door can be opened and closed manually. When power is restored, pull manual release a second time.
- If an EverCharge Unit is connected, the opener should be able to operate up to 20 times without power.

13. Door loses limits.

- Collar not tightened securely. Tighten collar (see Assembly Steps 1 and 2) and reprogram limits (see Adjustment Step 1).

14. The opener moves when the door is in operation:

- Some minor movement is normal for this product. If it is excessive the collar will wear prematurely.
- Check to make sure the torsion bar is not moving left/right excessively.
- Check to make sure the torsion bar is not visibly moving up and down as it rotates.
- Check that the opener is mounted at a right angle to the jackshaft. If not, move the position of the mounting bracket.

15. Power lock makes noise when operating.

- Call your local Merlin® dealer or Chamberlain customer service for replacement power lock.

OPERATION OF YOUR OPENER

Your merlin® Security+ opener and hand-held transmitter have been factory-set to a matching code which changes with each use, randomly accessing over 100 billion new codes. Your opener will operate with up to 64 merlin® Security+ transmitters and one Keyless Entry System. If you purchase a new transmitter, or if you wish to deactivate any transmitter, follow the instructions in the *Programming* section.

Activate your opener with any of the following:

- *The hand-held transmitter:* Hold top middle button down until the door starts to move.
- *The wireless wall button CM128* press and hold the large round button down until the door starts to move.
- *The Keyless Entry (See Accessories):* Must be programmed before use. See *Programming*.
- *Multi-Function Door Control*

When the opener is activated (with the safety reversing sensor correctly installed and aligned)

1. If open, the door will close. If closed, it will open.
2. If closing, the door will reverse.
3. If opening, the door will stop.
4. If the door has been stopped in a partially open position, it will close.
5. If obstructed while closing, the door will stop and reverse. The LED indicator light will flash.
6. If obstructed while opening, the door will stop.
7. If fully open, the door will not close when the beam is broken. The sensor has no effect in the opening cycle.

If the sensor is not installed, or is misaligned, the door won't close from a hand-held transmitter or wireless wall button. However, you can close the door with the multi-function door control, the Outside Keylock, or Keyless Entry, *if you activate them until down travel is complete*. If you release them too soon, the door will reverse.

CARE OF YOUR OPENER

MAINTENANCE SCHEDULE


Once a Month

- Manually operate door. If it is unbalanced or binding, call a trained door systems technician.
- Check to be sure door opens & closes fully. Adjust limits and/or force if necessary (see Adjustment Steps 1 and 2).
- Repeat the safety reverse test. Make any necessary adjustments (see Adjustment Step 5).


Once a Year

- Oil door rollers, bearings and hinges. The opener does not require additional lubrication. Do not grease the door tracks.


Using your C945 3ch Mini-Transmitter



Using your CM128 Wireless Wall Button



Using your Multi-Function Door Control



CHAMBERLAIN LIMITED WARRANTY

Merlin® Professional MJ3800

Sectional Garage Door Opener

Chamberlain Australia Pty Limited / Chamberlain New Zealand Limited (Chamberlain), the manufacturer of Merlin® automatic garage door openers, is committed to manufacturing and supplying high quality goods. As part of this commitment, we seek to provide reliable service and support for our goods and are pleased to provide you, the original purchaser, with this Chamberlain Limited Warranty.

The benefits given to you under this Chamberlain Limited Warranty are in addition to any rights and remedies that you may have under Australian or New Zealand consumer protection laws. Our goods come with guarantees that cannot be excluded under the Australian Consumer Law, or New Zealand Consumer Guarantees Act 1993. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

Chamberlain's warranty

What is covered

Chamberlain warrants to the original purchaser of the Merlin MJ3800 Sectional Door Opener (Unit) that all parts of the Unit, other than remote controlled transmitters, battery back up units and accessories, globes and batteries, are free from defects in materials and workmanship for a period of 24 months or 5,000 cycles (each opening & closing of the garage door equals 1 cycle) whichever comes first, from the date of purchase when installed by a Professional dealer appointed or authorised by Chamberlain in a residential premise with a residential specified garage door that is designed for the sole purpose of a single-family dwelling. Chamberlain warrants the motor component of the opener for 5 years or 15,000 cycles whichever comes first. Chamberlain warrants that remote controlled transmitters and accessories included with the Unit are free from defects in materials and workmanship for a period of 12 months from the date of purchase.

What is not covered

Batteries and globes are not covered under the Chamberlain Limited Warranty.

Travel costs incurred by Chamberlain or the Professional Dealer in either travelling to or from areas outside a capital city metropolitan area. These costs will be at the purchaser's expense.

Additional access costs incurred by a Professional Dealer or Chamberlain in obtaining access where the Unit is not readily accessible. These cost will be at the purchaser's expense.

Warranty Conditions

It is a condition of this Chamberlain Limited Warranty that the Unit is sold, installed and serviced by a Professional Dealer appointed or authorised by Chamberlain. A Merlin branded garage door opener purchased over the internet and installed by a person other than a Professional Dealer will not be covered by this Chamberlain Limited Warranty.

It is also a condition of this Chamberlain Limited Warranty that for the operating life of the Unit:

- 1 the garage door is spring balanced, is operable by hand and opens and closes with no more than a maximum of 20 kg of lifting weight;
- 2 the garage door and the Unit is professionally maintained and serviced by a Professional Dealer, at a minimum, during the third and fifth years of the Chamberlain Limited Warranty period such that the spring balanced door operates according to manufacturer specifications. If your door binds, sticks, or is out of balance, then it must not be used until serviced by a trained door technician or Professional Dealer. The garage door service fee will be at the purchaser's expense;
- 3 the warranty is registered by completing the online form at www.gomerlin.com.au or www.gomerlin.co.nz; and
- 4 you retain your sales docket or invoice as proof of purchase, and attach it to this manual to enable you to establish the date of purchase in the unlikely event of a warranty service being required.

Making a claim

During the applicable Chamberlain Limited Warranty period, if you are concerned that the Unit may be defective, call the Professional Dealer that sold/installed the opener, or our service centre on the toll free number below and a Chamberlain technician will diagnose the problem and arrange for this to be rectified. Once the problem has been diagnosed, subject to your rights under the applicable Australian and New Zealand consumer protection laws with respect to major failures, Chamberlain or its Professional Dealer will provide you with either, repairs to the Unit or a replacement Unit.

Repairs and replacement parts provided under this Chamberlain Limited Warranty are provided free of charge and are warranted for the remaining portion of the original warranty period.

This Chamberlain Limited Warranty provides benefits which are in addition to your other rights and remedies as a consumer.

114A4085F

Exclusions - what voids the warranty

If our service centre determines that a warranty claim has been made in respect of a failure or defect arising under or out of any exclusion detailed below such that the claim is not covered under this Chamberlain Limited Warranty, we may, subject to your other rights and remedies as a consumer, charge you a fee to repair, replace and/or return the Unit to you.

This Chamberlain Limited Warranty does not cover any failure of, or defect in, the Unit due to:

- 1 non-compliance with the instructions regarding specifications, installation, operation, maintenance and testing of the Unit or of any product with which the Unit is used;
- 2 any attempt by a person other than a Professional Dealer to repair, dismantle, reinstall or move the Unit to another location once it has been installed;
- 3 tampering, neglect, abuse, wear and tear, accident, electrical storm, excessive use or conditions other than normal domestic use;
- 4 problems with, or relating to, the garage door or garage door hardware, including but not limited to the door springs, door rollers, door alignment or hinges;
- 5 problems caused by electrical faults or replacement of batteries or light bulbs, blown fuses, electrical surges, power surges or power strikes, fire, flood, rain, water, lightning or storms;
- 6 water or moisture ingress that causes corrosion or electrical malfunction;
- 7 corrosion caused by sea air if located near a waterway, beach etc;
- 8 fitment to a commercial door or in a commercial operating application, installation of a residential garage door opener in a commercial or industrial premises other than a single-family dwelling.
- 9 lack of proper maintenance, service or care of the door and Unit;
- 10 any unauthorised modification to the Unit; or
- 11 damage caused by insects, pests or other after sale damage caused by events or accidents outside Chamberlain's reasonable control and not arising under normal and standard operating conditions.

NB: A General Purpose Outlet (GPO) ie: power point must be supplied by the consumer as this electrical fitting does not form a part of the Unit (opener).

If this Chamberlain Limited Warranty does not apply, you may have rights available to you under the Australian and New Zealand consumer protection laws.

Liability – Australia only

Except as set out in the Australian Consumer Law (being Schedule 2 of the *Competition and Consumer Act 2010*) (as amended, consolidated or replaced):

- 1 all other guarantees, warranties and representations in relation to the Unit or its supply are excluded to the extent that Chamberlain can lawfully exclude them; and
- 2 under no circumstances will Chamberlain be liable for consequential, incidental or special damages arising in connection with the use, or inability to use, the Unit, other than those which were reasonably foreseeable as liable to result from the failure.

Liability – New Zealand only

Except as set out in the *Fair Trading Act 1986 and the Consumer Guarantees Act 1993* (as amended, consolidated or replaced):

- 1 all other guarantees, warranties and representations in relation to the Unit or its supply are excluded to the extent that Chamberlain can lawfully exclude them; and
- 2 under no circumstances will Chamberlain be liable for consequential, incidental or special damages arising in connection with the use, or inability to use, the Unit, other than those which were reasonably foreseeable as liable to result from the failure.

Note

Chamberlain reserves the right to change the design and specifications of the Unit without prior notification. Some features or accessories of the Unit may not be available in certain markets or areas. Please check with your distributor.

Chamberlain service centre contact details

Australia

Phone toll free 1800 638 234

Fax toll free 1800 888 121

Website: gomerlin.com.au

Chamberlain Australia Pty. Ltd.

Unit1, 75 Epping Road

North Ryde NSW 2113

(PO BOX 1446, Lane Cove NSW 1595)

Email: customerservice@chamberlainanz.com

New Zealand

Auckland phone 09 477 2823

Phone toll free 0800 653 667

Fax toll free 0800 653 663

Website: gomerlin.co.nz

™ Trademark of The Chamberlain Group, Inc.

® Registered Trademark of The Chamberlain Group, Inc.

© 2015, The Chamberlain Group Inc.